

STOP

MODEL 555

12-60

12 Volt Hybrid Auto Radio Tubes that Require 12 Volts "B" Supply Cannot be Tested on this Tester.

0A2	22	2	33	147	S	5	1	5
0A3	15	2	31		S	5	1	5
0A4		1	37		S	5	4	5
0B2	17	2	19	457	S	1	1	1
0B3	17	2	36		S	5	1	5
0C3	18	2	35		S	5	1	5
0D3	22	2	30		S	5	1	5
0Z4-P 1		1	43		S	3-5	4	3
0Z4-P 2		1	43				4	5
1AB5	4	1	32	8	S	2-3-6	2	236
1AD4	3	5	0		S	1-2-4	3	124
1AE4	3	1	38	5	S	2-3-6	1	236
1AF4	4	1	32	5	S	2-3-6	2	236
1AF4-PEN	4	1	25		S	3-4-5-6	2	456
1AF5-DIO	4	1	0				3	3
1AG4	3	5	33		S	4-6-7	2	467
1AH4	3	3	33		S	4-6-7	2	467
1AJ5-PEN	3	4	25		S	3-5-6-7	2	367
1AJ5-DIO	3	4	45				4	5
1AX2	4	2	0	58	S	C	4	C
1B3/8016	4	2	20		S	C	4	C
1C21	13	2	35		S	5-7	1	57
1DN5-PEN	4	1	25	5	S	2-3-4-6	2	236
1DN5-DIO	4	1	0				2	4
1G3	4	2	22		S	C	4	C
1H2	4	2	10		S	C	4	C
1J3	4	2	5		S	C	4	C
1J5	5	2	30		S	3-4-5	2	345
1K3	4	2	5		S	C	4	C
1LA4	4	1	31		S	2-3-6	2	236
1LA6	4	1	29		S	2-3-4-5-6	2	23456
1LB4	4	1	31		S	2-3-6	2	236
1LC5	4	1	32		S	2-3-4-6	2	2346
1LC6	4	1	29		S	2-3-4-5-6	2	23456
1LD5-PEN	4	1	32		S	2-3-4-6	2	236
1LD5-DIO	4	1	0				3	4
1LE3	4	1	32		S	2-6	2	26
1LG5	4	1	33		S	2-3-4-6	2	2346
1LH4-TRI	4	1	31		S	2-4-6	2	26
1LH4-DIO	4	1	0				3	4
1LN5	4	1	32		S	2-3-4-6	2	2346
1N2	4	2	20		S	C	4	C
1N5	4	2	33		S	C-3-4	2	C34
16N-PEN	4	2	30		S	3-4-5-6	2	345
1N6-DIO	4	2	0				3	6
1R5	4	1	32	5	S	2-3-4-6	2	2346
1S2	4	2	25		S	C	4	C
1S4	4	5	35	16	S	2-3-4	2	234
1S5-PEN	4	1	28		S	3-4-5-6	2	456
1S5-DIO	4	1	0				3	3
1S6-PEN	3	5	0		S	1-3-6-8	3	138
1S6-DIO	3	5	10				3	6

5A18-PEN	8	5	39						2	6789
5AU4-P 1	8	2	42		H	8			1	6
5AU4-P 2	8	2	42						1	4
5AV8-TRI	8	4	37		H	5	S	2-3-6-8-9	2	23
5AV8-PEN	8	4	38						2	689
5AW4-P 1	8	2	42				S	4-6	1	4
5AW4-P 2	8	2	42						1	6
5AZ4-P 1	8	2	36				S	4-6	1	4
5AZ4-P 2	8	2	36						1	6
5B8-TRI	8	4	38		H	5	S	2-3-6-8-9	2	23
5B8-PEN	8	4	38						2	689
5BE8-TRI	8	4	38		H	5	S	1-2-6-7-9	2	12
5BE8-PEN	8	4	39						2	679
5BK7-TRI 1	8	4	38		H	5	S	1-2-6-7	2	12
5BK7-TRI 2	8	4	38						2	67
5BR8-TRI	8	4	38		H	5	S	1-2-6-7-9	2	12
5BR8-PEN	8	4	38						2	679
5BT8-PEN	8	4	38		H	5	S	1-2-6-7-8	2	678
5BT8-DIO 1	8	4	8						3	1
5BT8-DIO 2	8	4	8						3	2
5BZ7-TRI 1	9	4	38		H	5	S	1-2-6-7	2	67
5BZ7-TRI 2	9	4	38						2	12
5CG8-TRI	8	4	38	8	H	5	S	1-2-6-7-9	2	12
5CG8-PEN	8	4	39	8					2	679
5CL8-TRI	8	4	38		H	5	S	1-2-6-7-9	2	12
5CL8-TET	8	4	38						2	679
5CM8	8	4	38	8	H	5	S	1-3-9	2	139
5CM8-TRI	8	4	5		H	5	S	1-2-6-7-9	3	19
5CM8-PEN	8	4	10						3	267
5CZ5	8	4	42	6-8	H	5	S	1-3-9	1	139
5DH8-TRI	8	4	39		H	5	S	1-2-6-7-9	2	12
5DH8-PEN	8	4	39						2	679
5EA8-TRI	8	4	35		H	5	S	1-2-3-6-9	2	12
5EA8-PEN	8	4	36						2	369
5EB8-TRI	8	4	10		H	5	S	2-3-7-8-9	3	23
5EB8-PEN	8	4	45						1	789
5FV8-TRI	8	4	37		H	5	S	1-2	2	12
5FV8-PEN	8	4	37				S	6-7-9	2	679
5J6-TRI 2	8	3	44		H	4	S	1-2-5-6	1	16
5J6-TRI 1	8	3	44						1	25
5R4-P 1	8	2	40				S	4-6	1	6
5R4-P 2	8	2	40						1	4
5T4-P 1	8	2	43				S	4-6	1	4
5T4-P 2	8	2	43						1	6
5T8-TRI	8	4	39		H	5	S	1-2-6-8-9	1	89
5T8-DIO 1	8	4	20						3	6
5T8-DIO 2	8	4	20						3	2
5T8-DIO 3	8	4	20						3	1
5U4-P 1	8	2	40				S	4-6	1	4
5U4-P 2	8	2	40						1	6
5U8-TRI	8	4	45		H	5	S	1-2-3-6-9	1	19
5U8-PEN	8	4	45						1	236
5V3-P 1	8	2	40				S	4-6	1	4
5V3-P 2	8	2	40						1	6
5V4-P 1	8	2	44				S	4-6	1	4
5V4-P 2	8	2	44						1	6
5V6	8	2	42		H	7	S	3-4-5	1	345
5W4-P 1	8	2	36				S	4-6	1	4
5W4-P 2	8	2	36						1	6
5X3-P 1	8	1	36				S	2-3	1	2
5X3-P 2	8	1	36						1	3
5X4-P 1	8	8	41				S	3-5	1	3
5X4-P 2	8	8	41						1	5
5X8-TRI	8	5	44		H	4	S	2-3-7-8-9	1	23
5X8-PEN	8	5	38						2	789

